

The V2200Plus is a jump pack that takes on and prevents the unexpected. Offering 35 jumps on a full charge, smart clamps to protect against common safety hazards, and features a 300-lumen LED light. A built-in Bluetooth module supports 12V battery tests by pairing an app through Bluetooth, provides cranking and battery test reports, and replaces a battery before it dies. The V2200Plus can even act as a charging brick with the tool. Take the V2200Plus everywhere you go to be prepared for anything.

Features

- · Starts all 12V battery vehicles with up to 8.0L gas or 6L diesel engines in seconds
- · 2200A peak current
- $\boldsymbol{\cdot}$ Doubles as a wireless lead-acid battery tester through the tool's app
- · 6 safety protection measures
- \cdot The USB type-c port supports PD60W bidirectional quick charging
- · Multi-functional LED Light, Provides 3 illumination modes: Flashlight, SOS and Strobe
- \cdot USB Output for recharging smartphones, tablets, and more
- \cdot DC Output for powering 12V devices (air purifier and tire inflation, etc.)
- · 16000mAh Versatile Power Supply
- \cdot Load, No Load, and Ripple Voltage Tests
- · Charging Tests: Voltage, SOH, SOC, Internal Resistance
- $\cdot \ \mathsf{Cranking} \ \mathsf{Tests} \\ : \mathsf{Cranking} \ \mathsf{Time} \ \mathsf{and} \ \mathsf{Cranking} \ \mathsf{Voltage} \ \mathsf{Test} \\$
- · Battery Tests: Test CCA, Rated CCA, and Battery Health Status
- · Generates Jump Start Reports
- \cdot View jump-start time and voltage through the app

Specs

Dimensions: 267*157*106 mm (10.5*6.2*4.2 in.) Weight: 1460g (51.5 oz.) Peak Current: 2200A; 500A 2S Peak Current: 2200A; 500A 2S
Battery Capacity: 16000 mAh 3:7V; 59.2Wh
Input Port: Type-C:
Bidirectional, PD60W; 5V-3A, 9V-3A, 12V-3A, 15V-3A, 20V-3A
Output Ports: Type-C:
PD60W 20V-3A,15V-3A,12V-3A,9V-3A,5V-3A
USB1: QC18W,12V-1.5A,9V-2A,5V-3A
USB2: QC18W,12V-1.5A,9V-2A,5V-3A
DC: Max 16.8V-10A
Clamp Cable Lengths: 200mm (7.9 in.)
Jump Start Capacity: 8L Gas. 6L Diesel

Jump Start Capacity: 8L Gas, 6L Diesel Protections: Reverse connection, reverse charging, short circuits, over current, over temperature, over discharge Jump Volume: 35 Jumps On A Full Charge

What's In The Box

- · V2200Plus *1
- · Jump/Tester Clamps *1
- · USB Cable *1
- · Carry Case *1
- · Multilingual Menu *1



